


### **Electronics**


## Kilovac EV250-1A & 1B - 400 Amps ("Czonka II EVX")

Make & Break Load Switching





Note: Dimensions in inches. Multiply values by 25.4 for dimensions in mm.




For circuit conditions and actual data refer to the EV250 hot switch study. Since each application is unique, user is encouraged to verify rating in

PRODUCT SPECIFICATIONS					
Part Number	UNIT	EV250-1A	EV250-1B		
Contact Arrangement		SPST-NO	SPST-NO		
Contact Form		X	X		
Continuous Current Carry, Max	A	400	400		
6.5 Minutes	A	500	500		
Break Current @ 320 Vdc	Α	2,500	2,500		
Contact Resistance, Max	ohms	0.0003	0.0003		
Contact Resistance, Typ	ohms	0.0001 - 0.0002	0.0001 - 0.0002		
Dielectric at Sea Level (leakage < 1mA)	Vrms	2,200	2,200		
Shock, 11 ms 1/2 Sine (peak), operating	G's Peak	30	30		
Vibration, Sinusoidal (80-2000 Hz, peak)	G's	20	20		
Operating Ambient Temperature Range	℃	-40 to +85	-40 to +85		
Load Life, @320 Vdc, 95% Weibull*	cycles	See Page 19	See Page 19		
Operate Time, 25°C					
Close (includes bounce) Typ	ms	30	30		
Bounce (after close only), Max	ms	5	5		
Open (includes arcing), Max	ms	15	15		
Insulation Resistance @ 500 Vdc, Min	Mohm	100	100		
Weight, Nominal	pound (kg)	1.54 (0.7)	1.54 (0.7)		

Refer to Page 19 for actual mix of precharge and break currents used on each cycle.

#### Features:

- Hydrogen dielectric for power switching high current loads
- · 400 A carry, 2,500 A interrupt @ 320 Vdc
- · Ideal for circuit protection, control, battery switching, and main power safety disconnect
- Versatile power, voltage, and current operating range: 28-1800Vdc tested
- · Low-cost compact version for volume production applications. Requires external coil economizer (PWM or lower hold voltage)
- · Patented "hammer effect" mechanism breaks light contact welds
- Patented "Super-sealed" environment chamber uniquely protects ALL moving parts
- · Can operate in harsh environments
- · Moving contact rotates to provide fresh contact surface for low contact resistance and low power comsumption
- Sealed control connector. Mating connector with flying leads P/N 2005 available, see page 59
- · Logic control enabled by external economizer P/N 9913
- · High temperature (135°C) model with 10 inch flying leads available (-4A call factory for sales drawing)
- Bi-directional power switching
- Fast operate and release time



0011 0474						
COIL DATA***						
Parameter	EV250-1A	EV250-1B	Units			
Voltage* (nominal )	12	24	Vdc			
Pickup (close), max.	8.3	16.6				
Continuous Hold, max/min	** 5.1/3.8	10.2/7.6				
Dropout (open), min.	0.88 - 3.3	2.4 - 6.6				
Coil Resistance						
@ 25°C, +/- 10%	3	12	Ohms			
Coil Energy, max.	0.2	0.2	J			
Coil Clamping	3 x nom.	3 x nom.				

- \* Do not apply continously. Requires external coil economizer. Other special coil voltages available upon request.
- At maximum continuous current and maximum ambient temperature. Hold voltage must be maintained within the limits specified to keep contacts closed and to prevent coil overheating.

  \* Do not use a free wheeling diode or capacitor across the coil.

# PART NUMBER SELECTION


Sample Part No. EV250-1 Coil Voltage A = 12 Vdc, Nominal B = 24 Vdc, Nominal

For detailed specifications and recommendations, refer to the EV250-1A & B sales drawings.

# **EV250 Contact Ratings**

### **CURRENT vs TIME**

#### CONTACTS CLOSED INTO 70% AND 90% CAPACITOR PRE CHARGE



LIFE RATINGS AND QUALIFICATION TEST PLAN					
	Normal Operations	Abnormal Operations			
Test #	1	2	3	4	
Current	reference graph and		-250 A	2500 A	
Voltage	test circuit diagram (sht. 8)		320 V	320 V	
Load Type	Capacitive	Capacitive	Resistive	Resistive	
% Pre Charge	90%	70%	N/A	N/A	
Switch Mode	make	make	make/ break	break only	
	only	only		,	
Sequence		•			
1	10K cycles	10 cycles	2	2	
2	10K	10	2		
3	10K	10	2		
4	10K	10	2	2	
5	10K	10	2		
Etc.	Continue Cycling to Relay Failure				

The testing objective is to verify proper relay function for a given number of consecutive and cumulative cycles under both normal and abnormal conditions in a variety of load switching applications. The life rating of 40K cycles minimum was calculated with 95% Weibull reliability.

## Electrical Data (Over Temperature Range - Max. Terminal Temp. = 200°C)

Make/Break Life for Capacitive & Resistive Loads at 320 Vdc (	) (2)	
@ 90% capacitive pre-charge	Cycles	50,000
@ 70% capacitive pre-charge	Cycles	50
@ -250 A (2 consecutive, reverse polarity) (1)	Cycles	10
@ 3300 A (break only, 2 consecutive) (1)	Cycles	4
Mechanical Life	Cycles	100,000

<sup>(1)</sup> Resistive load includes inductance L = 25 uH. Load @ 2500 A tested @ 200 uH.

<sup>2)</sup> Conductor: 2 each of Copper 54 mm2 (AWG 0) required for > 250 A carry.

<sup>1</sup> Copper (AWG 0) conductor recommneded for ≤ 250 A

<sup>(3)</sup> Life based on projected Weibull Life with 95% Reliability